

## Clone a remote or copy and paste channel settings

**Copy Remote to another Remote**- P2, P2 on the current remote, then P2 on the new remote.

**Copy channel to another channel**- example program channel 1, then go to another channel not using (say Ch 15) program second shade. while on Channel 15

hit P2, P2. Then go back to channel 1 and hit P2, now it is copied to channel 1. This way you will copy CH1 to the shade that was programmed to CH15.

**Program multiple shades on one channel**- Option 1-Program the shade, when finished put that motor in "Mute/Sleep" mode. Do this by long pressing the program button on the head of the motor til it jogs for the 3rd time, then release it is now in sleep mode.

Option 2-Program a shade on say channel 2, then once complete turn off power to the motor (small black switch on motor head end-may be under metal cover), then program next shade on the same channel and so on. When complete turn all motors back on .